


NORGES TEKNISK-NATURVITENSKAPELIGE
UNIVERSITET

Cost efficient Lie group integrators in the RKMK class

by

Fernando Casas and Brynjulf Owren

PREPRINT
NUMERICS NO. 5/2002



NORWEGIAN UNIVERSITY OF SCIENCE AND
TECHNOLOGY
TRONDHEIM, NORWAY

This report has URL <http://www.math.ntnu.no/preprint/numerics/2002/N5-2002.ps>
Address: Department of Mathematical Sciences, Norwegian University of Science and Technology,
N-7491 Trondheim, Norway.

Cost efficient Lie group integrators in the RKMK class

Fernando Casas^{1*} Brynjulf Owren^{2†}

December 19, 2002

Abstract

In this work a systematic procedure is implemented in order to minimise the computational cost of the Runge–Kutta–Munthe-Kaas (RKMK) class of Lie-group solvers. The process consists of the application of a linear transformation to the stages of the method and the analysis of a graded free Lie algebra to reduce the number of commutators involved. We consider here RKMK integration methods up to order seven based on some of the most popular Runge–Kutta schemes.

¹Departament de Matemàtiques, Universitat Jaume I, 12071-Castellón, Spain.

²Department of Mathematical Sciences, NTNU, N-7491 Trondheim, Norway, and Center for Advanced Study, Drammensveien 78, 0271 Oslo, Norway.

AMS Subject Classification: 65L05

Key Words: time integration, geometric integration, numerical integration of ordinary differential equations on manifolds, numerical analysis, Lie algebras, Lie groups.

1 Introduction

The integration schemes of Munthe-Kaas [7] can be applied to differential equations on homogeneous manifolds

$$\dot{y} = f(y) \cdot y, \quad y(0) = y_0 \in \mathcal{M}. \quad (1)$$

Generally, (1) is induced by a transitive action by a Lie group G on \mathcal{M} , so that $f : \mathcal{M} \rightarrow \mathfrak{g}$ is a map from the manifold to the Lie algebra \mathfrak{g} of G . The product $Z \cdot m$, $Z \in \mathfrak{g}$, $m \in \mathcal{M}$ is then understood as

$$Z \cdot m = \left. \frac{d}{dt} \right|_{t=0} \exp(tZ) \cdot m.$$

A special case is when G is a subgroup of $GL(n)$, the Lie group of invertible $n \times n$ matrices and $\mathcal{M} = G$. Of particular interest in applications is the group $G = SO(n)$, the set of $n \times n$ orthogonal matrices. The corresponding Lie algebra $\mathfrak{g} = \mathfrak{so}(n)$ is the set of $n \times n$ skew-symmetric matrices, see also Iserles et al. [5] for more details.

*Email: casas@mat.uji.es

†Email: Brynjulf.Owren@math.ntnu.no

One may solve (1) by transforming the differential equation from \mathcal{M} to \mathfrak{g} . This was achieved by setting $y(t) = \exp(\sigma(t)) \cdot y_0$ with $\sigma(0) = 0$ in a neighborhood of $y_0 \in \mathcal{M}$ and then derive a differential equation for $\sigma(t)$. It is now well-known that one gets

$$\dot{\sigma} = d \exp_{\sigma}^{-1}(f(\exp(\sigma) \cdot y_0)) \quad (2)$$

The map $d \exp_u^{-1} : \mathfrak{g} \rightarrow \mathfrak{g}$ is expressed in terms of commutators through the infinite series

$$d \exp_u^{-1}(v) = \sum_{k=0}^{\infty} \frac{B_k}{k!} \text{ad}_u^k v = v - \frac{1}{2}[u, v] + \frac{1}{12}[u, [u, v]] + \dots \quad (3)$$

where $\text{ad}_u^0 v = v$, $\text{ad}_u^k v = [u, \text{ad}_u^{k-1} v]$ and B_k are the Bernoulli numbers. The idea of Munthe-Kaas was to approximate the solution of (2) by means of a classical Runge-Kutta method, and then transform the result $\sigma_1 \approx \sigma(h)$ back to \mathcal{M} by setting $y_1 = \exp(\sigma_1) \cdot y_0$. The series (3) can be truncated because it is used only in cases where the argument $u = \mathcal{O}(h)$. Using an explicit p th order Runge-Kutta method with s stages, one can write the corresponding Munthe-Kaas (RKMK) Lie group scheme in the following form, where h is the stepsize and a_{ij}, b_i are the Runge-Kutta parameters.

Algorithm 1.1

for $i = 1 : s$ **do**

$$u_i = \sum_{j=1}^{i-1} a_{ij} \text{dexpinv}(u_j, k_j, p - 1)$$

$$k_i = hf(\exp(u_i) \cdot y_0)$$

end do

$$v = \sum_i b_i \text{dexpinv}(u_i, k_i, p)$$

$$y_1 = \exp(v) \cdot y_0$$

Here $\text{dexpinv}(u, v, p)$ denotes a p th order approximation to $d \exp_u^{-1}(v)$, i.e. $d \exp_{tu}^{-1}(v) - \text{dexpinv}(tu, v, p) = \mathcal{O}(t^{p+1})$ for all $u, v \in \mathfrak{g}$ at $t = 0$. In [7] it was suggested that this approximation is obtained simply by truncating the series (3). Keeping in mind that the Bernoulli numbers with odd indices (except the first) vanish, one finds that the number of commutators to be computed in each step is $(p - 2)(s - 1)$ for p even and $(p - 1)(s - 1)$ for p odd. However, it was noted in [8] that substantial savings can be made for low order methods, by applying a linear transformation to the stages k_i in the algorithm. One introduces transformed variables

$$Q_i = \sum_{j=1}^i V_{i,j} k_j = \mathcal{O}(h^{q_i}), \quad i = 1, \dots, s, \quad (4)$$

where the constants V_{ij} are chosen such that the resultant integers q_i are as large as possible. Then, it is evident that commutators like

$$[Q_{i_1}, [Q_{i_2}, \dots, [Q_{i_{m-1}}, Q_{i_m}] \dots]] = \mathcal{O}(h^{q_{i_1} + \dots + q_{i_m}})$$

which makes it easy to discard terms of order higher than the method itself. The discussion of complexity in [8] is just based on counting the number of commutators N_2 whose order does not exceed that of the method. Their treatment depends on the particular Runge-Kutta method which is used, but for some of the most popular schemes we can deduce the following

table, where *Orig* indicates the number of commutators from the schemes of [7], whereas the column *FLA* is what one obtains from approach of [8].

Method	p	s	Orig	FLA
RK4	4	4	6	4
DOPRI5	5	6	20	12
Butcher6	6	7	24	26
Butcher7	7	9	48	60
RKF78	8	13	72	133

It is important to note that the numbers in the *FLA* column do not count the actual number of commutators that must be computed. For instance the expression $[Q_1, Q_2] + [Q_1, Q_3]$ would be counted as two commutators whereas in this case one only needs to compute the single commutator $[Q_1, Q_2 + Q_3]$. Still, the rapid increase in this number for higher orders led the authors of [8] to believe that their approach would lead to schemes with a reduced number of commutators only for the low and moderate order cases.

Recently, there has been some progress in reducing the complexity in integration schemes based on the Magnus series expansion. Iserles and Nørsett [6] have studied these methods extensively and also in [8] the question of reducing the number of commutators is addressed. In Celledoni et al. [3], the authors have tried to quantify the computational cost associated to various Lie group integrators. However, even more recently Blanes et al. [1] have found remarkable savings in computational complexity for Magnus series schemes compared to what was previously known, the optimal number of commutators for orders 4, 6 and 8 being 1, 3 and 6 respectively.

The aim of this paper is to combine the approach of [8] with that of [1] to obtain Lie group integrators in the RKMK class with significant reduction in the number of commutators compared to what is presently known. We start by a case study in section 2, where we consider methods of order 4 as a special illustration. The treatment of this case exhibits the main ideas, but involves little of the machinery of Butcher series and graded free Lie algebras needed to treat the full general case. In section 3, we extend and generalize the approach of [8] by using Butcher's order theory to obtain a suitable basis for the graded free Lie algebra associated with the stages of an explicit RKMK method. Then, in section 4 we present an approach for further minimizing the number of commutators.

2 Fourth-order RKMK methods. A case study

In this section we illustrate the main features of the procedure leading from Algorithm 1.1 to the construction of efficient Lie-group solvers for the nonlinear differential equation (1). As stated in the introduction, it consists of three parts: (i) first, one has to find the transformation (4); (ii) second, the internal stages u_i and v must be expressed in terms of the new variables Q_j provided by (4) and (iii) finally some optimization strategy has to be applied to reduce the total number of commutators involved and thus also the computational complexity of the algorithm.

In this process it is important to recall that, once u_i and v are expressed in terms of Q_m , they can be considered as elements of the graded free Lie algebra generated by $\{Q_i\}_{i \geq 1}$ with grades $w(Q_i) = q_i$, as suggested by (4) [8]. Therefore we can apply the optimization technique devised in [1] to write an element of a graded free Lie algebra with the minimum number of commutators. This will be particularly relevant for high order methods.

For simplicity, here we only consider 4th-order schemes and Algorithm 1.1 as applied to equation (1) defined in a matrix Lie group. Then $\exp(v) = e^v$ is the usual matrix exponential.

Lemma 2.1 *In the explicit RKMK Algorithm 1.1 one has for $i \geq 1$*

$$k_i = hf(y_0) + c_i h^2 f'(y_0) f(y_0) y_0 + \mathcal{O}(h^3) \quad (5)$$

$$u_i = c_i hf(y_0) + \mathcal{O}(h^2) \quad (6)$$

with $c_i = \sum_{j=1}^{i-1} a_{ij}$.

Proof: We use induction on the stage index. Let us denote $\tilde{k}_i \equiv d\exp_{u_i}^{-1}(k_i)$. It is clear that $u_i = 0$, $\tilde{k}_1 = k_1 = hf(y_0)$ and therefore $u_2 = a_{21}k_1 = c_2 hf(y_0)$. In general, suppose (6) is true for $i = l \geq 2$. Then, by expanding in Taylor series,

$$\begin{aligned} k_l &= hf(e^{u_l} y_0) = hf((I + u_l + \dots) y_0) = hf(y_0) + hf'(y_0) u_l y_0 + \mathcal{O}(h^3) \\ &= hf(y_0) + c_l h^2 f'(y_0) f(y_0) y_0 + \mathcal{O}(h^3). \end{aligned}$$

On the other hand, it is evident that $[u_l, k_l] = \mathcal{O}(h^3)$, so that $\tilde{k}_l = k_l + \mathcal{O}(h^3)$ and finally

$$\begin{aligned} u_{l+1} &= \sum_{j=1}^l a_{l+1,j} k_j + \mathcal{O}(h^3) = h \sum_{j=1}^l a_{l+1,j} f(y_0) + \mathcal{O}(h^2) \\ &= hc_{l+1} f(y_0) + \mathcal{O}(h^2) \end{aligned}$$

□

Proposition 2.2 *The linear combination $Q_i \equiv \sum_{j=1}^i V_{i,j} k_j = \mathcal{O}(h^3)$, $i \geq 3$, if and only if*

$$\sum_{j=1}^i V_{i,j} = 0 \quad \text{and} \quad \sum_{j=2}^i V_{i,j} c_j = 0 \quad (7)$$

Proof: From Lemma 2.1 we have

$$\begin{aligned} Q_i &= V_{i,1} hf(y_0) + \sum_{j=2}^i V_{i,j} (hf(y_0) + c_j h^2 f'(y_0) f(y_0) y_0 + \mathcal{O}(h^3)) \\ &= \left(\sum_{j=1}^i V_{i,j} \right) hf(y_0) + \left(\sum_{j=2}^i V_{i,j} c_j \right) h^2 f'(y_0) f(y_0) y_0 + \mathcal{O}(h^3) \end{aligned}$$

from which the result follows. We observe, in particular, that $Q_1 = k_1 = \mathcal{O}(h)$ and $Q_2 = V_{1,2}(-k_1 + k_2) = \mathcal{O}(h^2)$ if $c_2 \neq 0$. □

By solving (7), the first Q_i elements for any RKMK method are ($V_{i,i} = 1$)

$$\begin{aligned} Q_1 &= k_1 = \mathcal{O}(h) \\ Q_2 &= k_2 - k_1 = \mathcal{O}(h^2) \\ Q_3 &= k_3 - \frac{c_3}{c_2} k_2 + \frac{c_3 - c_2}{c_2} k_1 = \mathcal{O}(h^3) \\ Q_4 &= k_4 + V_{4,3} k_3 - \frac{c_4 + c_3 V_{4,3}}{c_2} k_2 - \frac{c_2 - c_4 + (c_2 - c_3) V_{4,3}}{c_2} k_1 = \mathcal{O}(h^3). \end{aligned} \quad (8)$$

The next step to build methods of order four with 4 stages is to rephrase Algorithm 1.1 in terms of Q_1, \dots, Q_4 and retain terms up to order $\mathcal{O}(h^3)$ in u_i , $1 \leq i \leq 4$, and up to order $\mathcal{O}(h^4)$ in v . This gives us

$$\begin{aligned}
u_1 &= 0 \\
u_2 &= c_2 Q_1 \\
u_3 &= c_3 Q_1 + a_{32} Q_2 - \frac{1}{2} a_{21} a_{32} [Q_1, Q_2] \\
u_4 &= c_4 Q_1 + \left(a_{42} + a_{43} \frac{c_3}{c_2} \right) Q_2 + a_{43} Q_3 \\
&\quad - \frac{1}{2} \left(a_{21} a_{42} - a_{32} a_{43} + a_{43} \frac{c_3^2}{c_2} \right) [Q_1, Q_2] \\
v &= Q_1 + \frac{1}{2c_2} Q_2 + (b_3 - b_4 V_{4,3}) Q_3 + b_4 Q_4 - \frac{1}{12c_2} [Q_1, Q_2] \\
&\quad + \frac{1}{2} (-2c_3 b_3 + b_3 + b_4 V_{4,3}) [Q_1, Q_3] - \frac{1}{2} b_4 [Q_1, Q_4]
\end{aligned} \tag{9}$$

Remarkably, the coefficient of $[Q_1, [Q_1, Q_2]]$ in v vanishes identically so that, in principle, with this formulation 3 commutators have to be computed (instead of 6 in terms of the k_i). In fact, if we denote

$$\begin{aligned}
d_1 &= [Q_1, Q_2] \\
d_2 &= [Q_1, (-2c_3 b_3 + b_3 + b_4 V_{4,3}) Q_3 - b_4 Q_4]
\end{aligned} \tag{10}$$

then

$$v = Q_1 + \frac{1}{2c_2} Q_2 + (b_3 - b_4 V_{4,3}) Q_3 + b_4 Q_4 - \frac{1}{12c_2} d_1 + \frac{1}{2} d_2 \tag{11}$$

involves only 2 commutators. The final algorithm requiring the minimum number of commutators is as follows:

Algorithm 2.3

for $i = 1 : 4$ **do**

u_i given by (9)

$k_i = hf(\exp(u_i) \cdot y_0)$

Q_i given by (8)

end do

v given by (11)

$y_1 = \exp(v) \cdot y_0$

Remarks:

1. We can fix the parameter $V_{4,3} \equiv \alpha$ so that $d_2 = -b_4 [Q_1, Q_4]$.
2. One could consider 4th-order Runge–Kutta methods with more than four stages. Even then the resulting RKMK algorithm in terms of the Q_i requires the computation of only 2 commutators as long as $Q_i = \mathcal{O}(h^3)$ for $i \geq 3$. For in this case u_i , $i = 3, \dots, s$, involves only $[Q_1, Q_2]$ and the commutators $[Q_1, [Q_1, Q_2]]$, $[Q_1, Q_3]$, $[Q_1, Q_4]$, $[Q_1, Q_5]$, etc., appearing in v can be grouped together.

3 Search for the optimal transformation

3.1 General considerations

As it has been clearly established in the preceding section, in the search for optimal schemes it is crucial one can find transformations Q_i of the stages with as high order as possible as in (4). In the following we generalize Proposition 2.2 and develop a systematic procedure to obtain this transformation for any classical Runge–Kutta scheme. The following result from [8] is useful for this purpose.

Proposition 3.1 *Suppose that there exists real numbers r_1, \dots, r_s such that*

$$\sum_{j=1}^s r_j d \exp_{u_i}^{-1} k_j = \mathcal{O}(h^q)$$

for some integer q , where u_i, k_j, h are as in Algorithm 1.1. Then

$$\sum_{j=1}^s r_j k_j = \mathcal{O}(h^q).$$

The result also applies when $\tilde{k}_i := d \exp_{u_i}^{-1}(k_i)$ is replaced by its p th order approximation as in Algorithm 1.1 as long as $q \leq p$. Since u_i, \tilde{k}_i and v are obtained from applying a classical Runge–Kutta method, we can use the Butcher theory [2]. We will here apply this theory by using the notation from [4], known as the B -series approach. We work in a somewhat simpler setting than the general case, because it is always true that the initial value in (2) is zero. The quantities u_i, v as well as the stage derivatives \tilde{k}_i can be formally expressed in a B -series expansion, $u_i = B(\mathbf{u}_i)$, $\tilde{k}_i = B(\tilde{\mathbf{k}}_i)$, $v = B(\mathbf{v})$ where in general B is defined as

$$B(\mathbf{a}) = \sum_{\tau \in T} \frac{h^{|\tau|}}{|\tau|!} \mathbf{a}(\tau) F(\tau)(0). \quad (12)$$

Here, T is the set of *rooted trees*, where $\tau \in T$ has $|\tau|$ nodes. The map $\mathbf{a} : T \rightarrow \mathbb{R}$ represents the coefficients of the B -series. The elementary differentials $F(\tau)$ depend on the derivatives of the right hand side of (2) evaluated at 0. An element of T is either the one-node tree which we simply denote by 1, or it is formed as $\tau = [\tau_1, \dots, \tau_\mu]$ where each $\tau_i \in T$. This is the tree obtained by joining the roots of the trees τ_1, \dots, τ_μ to a new common root. Consequently, $|\tau| = 1 + |\tau_1| + \dots + |\tau_\mu|$. The coefficients in the B -series for u_i, \tilde{k}_i , and v are related as follows:

$$\begin{aligned} \tilde{\mathbf{k}}_i(1) &= 1, & \text{and for } \tau = [\tau_1, \dots, \tau_\mu] \\ \mathbf{u}_i(\tau) &= \sum_{j=1}^s a_{ij} \tilde{\mathbf{k}}_j(\tau), \quad \tilde{\mathbf{k}}_i(\tau) = |\tau| \mathbf{u}_i(\tau_1) \cdots \mathbf{u}_i(\tau_\mu), \quad \mathbf{v}(\tau) = \sum_{j=1}^s b_j \tilde{\mathbf{k}}_j(\tau) \end{aligned} \quad (13)$$

In view of Proposition 3.1 we will, for each $i = 1, \dots, s$, search for constants r_1, \dots, r_i such that

$$\sum_{j=1}^i r_j \tilde{k}_j = \mathcal{O}(h^{q_i}),$$

where q_i is as large as possible. We shall always assume in this expression that $r_i = 1$. Thus, for $i = 1$ we get $q_1=1$. However, for $i > 1$ we obtain from (12) the conditions

$$\sum_{j=1}^i r_j \tilde{\mathbf{k}}_j(\tau) = 0, \quad \forall \tau \text{ such that } |\tau| \leq q_i - 1. \quad (14)$$

To proceed, it is instructive to enumerate the trees, increasingly in terms of $|\tau|$ and consider the matrix corresponding to (14)

$$\begin{bmatrix} 1 & 1 & 1 & \cdots & 1 \\ \hline 0 & c_2 & c_3 & \cdots & c_i \\ \hline 0 & c_2^2 & c_3^2 & \cdots & c_i^2 \\ \hline 0 & 0 & a_{32}c_2 & \cdots & \sum_j a_{ij}c_j \\ \hline \vdots & \vdots & \vdots & & \vdots \\ \hline \vdots & \vdots & \vdots & & \vdots \end{bmatrix} \quad (15)$$

The horizontal lines are distinguishing the orders. Denoting by N_q the number of conditions for order $\leq q$, one has

$$\begin{array}{c|cccccccc} q & 1 & 2 & 3 & 4 & 5 & 6 & 7 & 8 \\ \hline N_q & 1 & 2 & 4 & 8 & 17 & 37 & 85 & 200 \end{array}$$

We let $\mathbf{K}_{i,q}$ be the $N_q \times i$ matrix whose rows correspond to all trees such that $|\tau| \leq q$. For a given set of Runge–Kutta coefficients (a_{ij}) , the construction of the transformation (4) is not difficult, the following algorithm gives the lower triangular matrix V as well as the grades (q_1, \dots, q_s) .

Algorithm 3.2

```

V1,1 := 1
for i = 2 : s do
  q = 1
  while rank(Ki,q) = rank(Ki-1,q) do
    q = q + 1
  end while
  qi = q
  Solve Ki-1,q-1r = -si
  Set (Vi,1, ..., Vi,i-1) = rT, Vi,i = 1
end for
where si is the ith column of Ki,q.

```

Let us now turn to the general case of an s -stage p th order explicit irreducible Runge–Kutta method. We always scale the transformation by setting $V_{i,i} = 1$ in (4).

3.2 Analysis stage by stage

First stage. The first transformed stage is $Q_1 = k_1 = \mathcal{O}(h)$.

Second stage. Considering the first row of (15), we see that $Q_2 = k_2 - k_1 = \mathcal{O}(h^2)$, and no more can be achieved since $c_2 \neq 0$ in irreducible schemes.

Third stage. Considering the first two rows of (15) one finds that

$$Q_3 = \frac{c_3 - c_2}{c_2} k_1 - \frac{c_3}{c_2} k_2 + k_3 = \mathcal{O}(h^3)$$

This is the best one can do, because by imposing the conditions for the next order one finds that the third stage will coincide with either the first or the second stage, i.e. a reducible method.

Fourth stage. As we have shown in section 2, for this stage one obtains a one-parameter family of grade 3 vectors

$$Q_4 = \frac{c_4 - c_2 + \alpha(c_3 - c_2)}{c_2} k_1 - \frac{c_4 + \alpha c_3}{c_2} k_2 + \alpha k_3 + k_4 + \mathcal{O}(h^3).$$

However, to obtain grade 4 it is necessary to force the 4×4 matrix $\mathbf{K}_{4,3}$ to be singular. We define $\phi_i = \sum_j a_{ij} c_j$ and note that $\phi_1 = \phi_2 = 0$. Using $c_2 \neq 0$ we impose

$$\begin{vmatrix} 1 & c_3 & c_4 \\ c_2 & c_3^2 & c_4^2 \\ 0 & \phi_3 & \phi_4 \end{vmatrix} = c_4(c_2 - c_4)\phi_3 + c_3(c_3 - c_2)\phi_4 = 0. \quad (16)$$

1. *Methods of order 4 with 4 stages.* Unfortunately, this condition is incompatible with the corresponding RK scheme of 4 stages having order 4. To see this, we note for instance from [4] that for such schemes $c_4 = 1$ and we invoke the two order conditions

$$b_3\phi_3 + b_4\phi_4 = \frac{1}{6}, \quad b_3c_3\phi_3 + b_4\phi_4 = \frac{1}{8}. \quad (17)$$

Since $\phi_3 = a_{32}c_2$ is nonzero, we must impose from (16) the (necessary) condition

$$\begin{vmatrix} b_3 & b_4 & \frac{1}{6} \\ b_3c_3 & b_4 & \frac{1}{8} \\ c_2 - 1 & c_3(c_3 - c_2) & 0 \end{vmatrix} = \frac{1}{24}(c_3(4c_3 - 3)(c_3 - c_2)b_3 + (1 - c_2)b_4) = 0. \quad (18)$$

Finally, we combine the quadrature conditions

$$\sum_i b_i c_i^{q-1} = \frac{1}{q}, \quad q = 2, 3, 4$$

with (18) and we get at last the (necessary) condition

$$\begin{vmatrix} 1 & c_3 & 1 & \frac{1}{2} \\ c_2 & c_3^2 & 1 & \frac{1}{3} \\ c_2^2 & c_3^3 & 1 & \frac{1}{4} \\ 0 & c_3(4c_3 - 3)(c_3 - c_2) & 1 - c_2 & 0 \end{vmatrix} = \frac{1}{6}c_2c_3(1 - c_2)(1 - c_3)(c_2 - c_3) = 0.$$

There are only three possible cases of coinciding node values: [4, p. 138] $(c_2, c_3) = (1/2, 0), (1/2, 1/2)$ and $(1, 1/2)$. The first two are incompatible with (16) and the last one would require $\phi_4 = 0$ and thereby contradict the two conditions (17).

2. *Methods of order 5 with 6 stages.* For 5th order methods there are 17 order conditions. Imposing the simplifying assumption $\phi_i = \frac{1}{2}c_i^2$, $i \neq 2$, one finds that either $c_4 = 0$ or $c_4 = c_3$ for the fourth stage to have grade 4. A long and fairly technical analysis shows that these conditions are incompatible with the 17 order conditions for order 5. We have not pursued the question of whether it is possible to obtain 5th order methods with 6 stages such that the fourth stage has grade 4. However, for every known method of order 5 we have looked at, $Q_4 = \mathcal{O}(h^3)$ is the best that can be achieved.

In general, by adding enough stages, one can always achieve $Q_4 = \mathcal{O}(h^4)$, but the extra cost seems not to be compensated by the possible reduction in commutator calculations.

*i*th stage, $i > 4$. As long as $\mathbf{K}_{4,3}$ is non-singular one can easily achieve grade 3 for each Q_i where $i \geq 3$, in fact, one will always have $i - 3$ free parameters for these transformed stages. To completely characterize the highest attainable grade for subsequent stages seems complicated and perhaps not very useful because one may in this way easily exclude the most popular of the classical Runge–Kutta schemes. However, in [4, p. 155-156] we can find an explicit procedure for constructing 5th order schemes with 6 stages. The free parameters are c_2, c_3, c_4, c_5 and $a_{42} = \lambda$. It is easy to deduce that by leaving the free parameters unrestricted, the grade sequence will be (1, 2, 3, 3, 4, 4). The transformed stages Q_1, \dots, Q_4 must be chosen as described above, whereas

$$Q_5 = k_5 - \frac{c_5(c_5 - c_3)}{c_4(c_4 - c_3)}k_4 + \frac{c_5(c_5 - c_4)}{c_3(c_4 - c_3)}k_3 - \frac{(c_5 - c_3)(c_5 - c_4)}{c_3c_4} = \mathcal{O}(h^4)$$

and it is impossible to achieve higher grade. For the sixth stage, one can set $Q_6 = \sum_{i=1}^6 r_i k_i$, where $r_2 = 0$, $r_6 = 1$, and r_1, r_3, r_4, r_5 results from solving the system

$$\sum_{i=1}^5 r_i c_i^{q-1} = -1, \quad q = 1, 2, 3, 4.$$

Then Q_6 has grade 4. But demanding that

$$a_{4,2} = \lambda = \frac{1}{8} \frac{c_3^2 (15c_3^2 - 12c_3 + 2)}{c_2 (5c_3^2 - 4c_3 + 1)^3} \quad \text{and} \quad c_4 = \frac{1}{2} \frac{c_3}{5c_3^2 - 4c_3 + 1}$$

one obtains $Q_6 = \mathcal{O}(h^5)$. The Runge–Kutta–Fehlberg method of order 5 presented below does not fall within this class because $c_6 = \frac{1}{2} \neq 1$, but the Dormand–Prince method does.

3.3 Some examples of high order methods

We present here some of the most used explicit Runge–Kutta methods/pairs and give for each of them the transformation matrix V and the grade sequence (q_1, \dots, q_s) so that $Q_i = \sum_{j=1}^i V_{i,j} k_j = \mathcal{O}(h^{q_i})$.

5th-order

RKF45, Runge–Kutta–Fehlberg pair. The coefficients can be found in [4, p. 177]. The best possible sequence of grades for this method is (1, 2, 3, 3, 4, 5) and the corresponding transformation matrix is

$$V = \begin{bmatrix} 1 & & & & & & \\ -1 & 1 & & & & & \\ \frac{1}{2} & -\frac{3}{2} & 1 & & & & \\ \frac{35}{13} & -\frac{48}{13} & 0 & 1 & & & \\ -\frac{5}{36} & 0 & \frac{64}{171} & -\frac{845}{684} & 1 & & \\ \frac{11}{144} & 0 & -\frac{704}{855} & -\frac{2197}{2736} & \frac{11}{20} & 1 & \end{bmatrix} \quad (19)$$

DOPRI5(4), a method of Dormand and Prince. The coefficients of this widely used 7-stage pair can be found also in [4, p. 178]. In this case the grade sequence is (1, 2, 3, 3, 4, 4, 5) and the transformation matrix is

$$V = \begin{bmatrix} 1 & & & & & & \\ -1 & 1 & & & & & \\ \frac{1}{2} & -\frac{3}{2} & 1 & & & & \\ 0 & 5 & -6 & 1 & & & \\ -\frac{53}{243} & 0 & \frac{128}{243} & -\frac{106}{81} & 1 & & \\ 0 & 0 & -\frac{4}{53} & \frac{7}{4} & -\frac{567}{212} & 1 & \\ -\frac{71}{1440} & 0 & \frac{568}{3339} & -\frac{71}{48} & \frac{17253}{8480} & -\frac{176}{105} & 1 \end{bmatrix} \quad (20)$$

6th-order

A 6th-order method of Butcher. The coefficients of this method are found for instance by choosing the abscissae $c_2 = \frac{1}{2}$, $c_3 = \frac{2}{3}$, $c_5 = \frac{5}{6}$ and $c_6 = \frac{1}{6}$, and then follow the recipe in Butcher [2, p. 200-204]. The grade sequence is (1, 2, 3, 3, 4, 5, 4) and the transformation matrix is given by

$$V = \begin{bmatrix} 1 & & & & & & \\ -1 & 1 & & & & & \\ \frac{1}{3} & -\frac{4}{3} & 1 & & & & \\ 0 & -2 & 1 & 1 & & & \\ -\frac{3}{8} & 0 & -\frac{15}{8} & \frac{5}{4} & 1 & & \\ -\frac{3}{10} & 0 & \frac{1}{2} & -1 & -\frac{1}{5} & 1 & \\ -10 & 0 & 0 & -15 & 0 & 24 & 1 \end{bmatrix} \quad (21)$$

where $H_{i,j}$ denotes the j th element of the set \mathcal{H}_i , obtain an approximate expression for Z up to grade s involving the minimum number of commutators.

The procedure to solve this problem commences by taking the most general commutator one can build with elements of the set $\{Q_1, Q_2, \dots, Q_n\}$ such that $w(Q_n) = s$,

$$d_1 = \left[\sum_{i=1}^n a_{1,i} Q_i, \sum_{j=1}^n b_{1,j} Q_j \right].$$

For explicit RKMK methods, in general $n \geq s$. Next we write the most general commutator one can form with $\{Q_1, Q_2, \dots, Q_n, d_1\}$,

$$d_2 = \left[\sum_{i=1}^n a_{2,i} Q_i + a_{2,p+1} d_1, \sum_{j=1}^n b_{2,j} Q_j + b_{2,p+1} d_1 \right]$$

and the action is repeated recursively r times to reproduce the term $[Q_1, [Q_1, \dots [Q_1, Q_2]]]$, i.e., the term $H_{s,j}$ of \mathcal{H}_s which involves the greatest number of nested commutators (if the corresponding coefficient $\alpha_{s,j} \neq 0$). The problem is reduced then to determine the coefficients $a_{i,j}$, $b_{i,j}$, α_i , γ_i such that

$$Z = \sum_{i=1}^n \alpha_i Q_i + \sum_{i=1}^r \gamma_i d_i + \Theta(s+1),$$

where $\Theta(s+1)$ represents terms in \mathcal{L}_Q of grade $s+1$ or higher. This results in a nonlinear system of algebraic equations in the coefficients with no guarantee to have real solutions. If there are, then the minimum number of commutators required is precisely r . Otherwise, additional commutators d_{r+1} , etc. must be included in Z . In any case the number of variables to be determined grows tremendously with the grade, so that some simplifying assumptions must be introduced. In this respect it is useful to take into account whatever symmetry properties the element Z has [1].

For the particular class of explicit RKMK schemes with s stages one has a sequence of elements Z_i , $i = 1, \dots, s+1$ in \mathcal{L}_Q (the internal stages u_i and v) to approximate with the minimum number of commutators and, in addition, the evaluation of Z_1, \dots, Z_{i-1} is required for computing Z_i . This imposes severe restrictions on the optimization procedure so that, in general, the optimal number of commutators is much higher than the minimum number required to approximate each individual term in the algorithm.

4.2 Optimization of DVERK

As an illustration of the above procedure we next consider Verner's method of order 6(5) (DVERK) and try to minimize the number of commutators in the corresponding RKMK scheme. When the transformation (4) with matrix (22) is applied to the internal stages $u_i = \sum_{j=1}^{i-1} a_{ij} \text{dexpinv}(u_j, k_j, 5)$, $i = 1, \dots, 8$ and $v = \sum_{i=1}^8 b_i \text{dexpinv}(u_i, k_i, 6)$ in Algorithm

1.1, we obtain (up to order $\mathcal{O}(h^5)$ in u_i and $\mathcal{O}(h^6)$ in v)

$$\begin{aligned}
u_1 &= 0 \\
u_2 &= \frac{1}{6}Q_1 \\
u_3 &= \frac{4}{15}Q_1 + \frac{16}{75}Q_2 - \frac{4}{225}[1, 2] + \frac{1}{2025}[1, 1, 2] \\
u_4 &= \frac{2}{3}Q_1 + \frac{4}{3}Q_2 + \frac{5}{2}Q_3 - \frac{2}{45}[1, 2] - \frac{1}{3}[1, 3] \\
&\quad - \frac{67}{4050}[1, 1, 2] + \frac{2}{135}[1, 1, 3] + \frac{13}{8100}[1, 1, 1, 2] - \frac{4}{15}[2, 3] - \frac{88}{3375}[2, 1, 2] \\
u_5 &= \frac{5}{6}Q_1 + \frac{25}{12}Q_2 - \frac{425}{64}Q_3 + \frac{85}{96}Q_4 - \frac{31}{48}[1, 2] + \frac{255}{128}[1, 3] - \frac{85}{288}[1, 4] \\
&\quad + \frac{409}{4320}[1, 1, 2] - \frac{119}{384}[1, 1, 3] + \frac{85}{2592}[1, 1, 4] - \frac{731}{77760}[1, 1, 1, 2] + \frac{493}{96}[2, 3] \\
&\quad - \frac{85}{144}[2, 4] + \frac{493}{4050}[2, 1, 2] \\
u_6 &= Q_1 + 3Q_2 + \frac{55}{9}Q_3 + \frac{11}{36}Q_4 + \frac{88}{255}Q_5 - \frac{17}{90}[1, 2] - \frac{319}{144}[1, 3] - \frac{997}{8100}[1, 1, 2] \\
&\quad - \frac{22}{153}[1, 5] + \frac{23683}{38880}[1, 1, 3] - \frac{187}{3888}[1, 1, 4] + \frac{1837}{48600}[1, 1, 1, 2] - \\
&\quad \frac{32351}{4320}[2, 3] + \frac{143}{432}[2, 4] - \frac{42031}{81000}[2, 1, 2] \\
u_7 &= \frac{1}{15}Q_1 + \frac{1}{75}Q_2 - \frac{5}{4}Q_3 + \frac{9}{100}Q_4 + \frac{2484}{10625}Q_5 - \frac{29}{450}[1, 2] - \frac{557}{600}[1, 3] + \\
&\quad \frac{39}{1000}[1, 4] - \frac{10271}{202500}[1, 1, 2] - \frac{207}{2125}[1, 5] + \frac{89957}{216000}[1, 1, 3] - \frac{443}{12000}[1, 1, 4] \\
&\quad + \frac{36977}{1620000}[1, 1, 1, 2] - \frac{121999}{24000}[2, 3] + \frac{1209}{4000}[2, 4] - \frac{408037}{1350000}[2, 1, 2] \\
u_8 &= Q_1 + 3Q_2 + \frac{1375}{258}Q_3 + \frac{187}{516}Q_4 + \frac{220}{731}Q_5 + \frac{3850}{26703}Q_7 - \frac{59}{258}[1, 2] - \\
&\quad \frac{935}{516}[1, 3] - \frac{11}{344}[1, 4] - \frac{2377}{23220}[1, 1, 2] - \frac{1881}{18275}[1, 5] + \frac{30107}{74304}[1, 1, 3] - \\
&\quad \frac{407}{12384}[1, 1, 4] + \frac{75823}{2786400}[1, 1, 1, 2] - \frac{46981}{8256}[2, 3] + \frac{275}{1376}[2, 4] - \frac{198583}{464400}[2, 1, 2] \\
v &= Q_1 + 3Q_2 + \frac{3}{4}Q_4 + \frac{12}{85}Q_5 + \frac{3}{44}Q_6 + \frac{43}{616}Q_8 - \frac{1}{2}[1, 2] + \frac{25}{96}[1, 3] - \\
&\quad \frac{11}{48}[1, 4] - \frac{4}{85}[1, 5] - \frac{3}{88}[1, 6] - \frac{5}{192}[1, 1, 3] + \frac{1}{96}[1, 1, 4] + \frac{1}{120}[1, 1, 1, 2] + \\
&\quad \frac{15}{16}[2, 3] - \frac{3}{8}[2, 4] - \frac{3}{20}[2, 1, 2] + \frac{25}{2484}[1, 7] + \frac{1}{425}[1, 1, 5] + \frac{1}{176}[1, 1, 6] \\
&\quad - \frac{5}{1152}[1, 1, 1, 3] + \frac{11}{2880}[1, 1, 1, 4] + \frac{1}{20}[1, 2, 1, 2] - \frac{36}{425}[2, 5] - \frac{9}{88}[2, 6] \\
&\quad - \frac{5}{64}[2, 1, 3] - \frac{1}{160}[2, 1, 4] - \frac{15}{64}[3, 4] + \frac{5}{32}[3, 1, 2] - \frac{1}{10}[4, 1, 2]
\end{aligned}$$

where $[i_1, i_2, \dots, i_{l-1}, i_l]$ stands for the nested commutator $[Q_{i_1}, [Q_{i_2}, \dots [Q_{i_{l-1}}, Q_{i_l}]]]$. On the other hand, the expression of v for the embedded method reads

$$\begin{aligned} \hat{v} = & Q_1 + 3Q_2 + \frac{3}{4}Q_4 + \frac{12}{85}Q_5 + \frac{3}{44}Q_6 - \frac{1}{2}[1, 2] + \frac{25}{96}[1, 3] - \frac{11}{48}[1, 4] - \frac{4}{85}[1, 5] - \frac{3}{88}[1, 6] \\ & - \frac{5}{192}[1, 1, 3] + \frac{1}{96}[1, 1, 4] + \frac{1}{120}[1, 1, 1, 2] + \frac{15}{16}[2, 3] - \frac{3}{8}[2, 4] - \frac{3}{20}[2, 1, 2] + \frac{1}{765}[1, 1, 5] \\ & + \frac{1}{176}[1, 1, 6] + \frac{1}{20736}[1, 1, 1, 3] + \frac{37}{10368}[1, 1, 1, 4] + \frac{229}{972000}[1, 1, 1, 1, 2] + \frac{127}{2700}[1, 2, 1, 2] \\ & - \frac{13}{170}[2, 5] - \frac{9}{88}[2, 6] - \frac{461}{3456}[2, 1, 3] - \frac{5}{1728}[2, 1, 4] - \frac{95}{384}[3, 4] + \frac{299}{1728}[3, 1, 2] \\ & - \frac{217}{2160}[4, 1, 2]. \end{aligned}$$

We observe that u_3 requires the evaluation of the commutators

$$d_1 = [Q_1, Q_2], \quad d_2 = [Q_1, d_1] \quad (25)$$

so that

$$u_3 = \frac{4}{15}Q_1 + \frac{16}{75}Q_2 - \frac{4}{225}d_1 + \frac{1}{2025}d_2. \quad (26)$$

In u_4 we have the commutators $[Q_1, Q_3]$ and $[Q_1, [Q_1, Q_3]]$ which cannot be generated from u_3 . Thus we introduce

$$d_3 = [Q_1, Q_3] \quad (27)$$

and the new commutator

$$d_4 = \left[\sum_{i=1}^3 a_{4,i} Q_i + \sum_{i=4}^6 a_{4,i} d_{i-3}, \sum_{j=1}^3 b_{4,j} Q_j + \sum_{j=4}^6 b_{4,j} d_{j-3} \right] \quad (28)$$

to reproduce the remaining terms. In fact, most of the coefficients in (28) are redundant: with

$$d_4 = \left[Q_1 + Q_2, -\frac{4}{15}Q_3 - \frac{88}{3375}d_1 + \frac{13}{8100}d_2 + \frac{2}{135}d_3 \right] \quad (29)$$

we have

$$u_4 = \frac{2}{3}Q_1 + \frac{4}{3}Q_2 + \frac{5}{2}Q_3 - \frac{2}{45}d_1 + \frac{193}{20250}d_2 - \frac{1}{15}d_3 + d_4. \quad (30)$$

In the same way, at least two additional commutators are needed to write u_5 because $[Q_1, Q_4]$ and $[Q_1, [Q_1, Q_4]]$ cannot be generated as a linear combination of d_1, \dots, d_4 . Thus we introduce

$$d_5 = [Q_1, Q_4] \quad (31)$$

and a new commutator d_6 to reproduce the terms $[Q_1, [Q_1, Q_3]]$, $[Q_1, [Q_1, Q_4]]$, $[Q_2, Q_3]$, $[Q_2, Q_4]$, $[Q_1, [Q_1, [Q_1, Q_2]]]$ and $[Q_2, [Q_1, Q_2]]$ in u_5 . This can be achieved if

$$d_6 = [Q_1 + Q_2, b_{6,3}Q_3 + b_{6,4}Q_4 + b_{6,5}d_1 + b_{6,6}d_2 + b_{6,7}d_3 + b_{6,9}d_5] \quad (32)$$

with coefficients

$$b_{6,3} = \frac{493}{96}, \quad b_{6,4} = -\frac{85}{144}, \quad b_{6,5} = \frac{493}{4050}, \quad b_{6,6} = -\frac{731}{77760}, \quad b_{6,7} = -\frac{119}{384}, \quad b_{6,9} = \frac{85}{2592}.$$

Finally

$$u_5 = \frac{5}{6}Q_1 + \frac{25}{12}Q_2 - \frac{425}{64}Q_3 + \frac{85}{96}Q_4 - \frac{31}{48}d_1 - \frac{1753}{64800}d_2 - \frac{1207}{384}d_3 + \frac{85}{288}d_5 + d_6. \quad (33)$$

In the expression of u_6 one has the commutator $[Q_1, Q_5]$, which cannot be expressed as a linear combination of d_1, \dots, d_6 . Thus we need to include at least one additional commutator d_7 . With

$$d_7 = \left[Q_1 + Q_2, -\frac{32351}{4320}Q_3 + \frac{143}{432}Q_4 - \frac{22}{153}Q_5 - \frac{42031}{81000}d_1 + \frac{1837}{48600}d_2 + \frac{23683}{38880}d_3 - \frac{187}{3888}d_5 \right] \quad (34)$$

then

$$u_6 = Q_1 + 3Q_2 + \frac{55}{9}Q_3 + \frac{11}{36}Q_4 + \frac{88}{255}Q_5 - \frac{17}{90}d_1 + \frac{10687}{27000}d_2 + \frac{22781}{4320}d_3 - \frac{143}{432}d_5 + d_7. \quad (35)$$

The expressions of u_7 and u_8 do not contain additional commutators so that, in principle, one could express them as linear combinations of d_1, \dots, d_7 . This turns out to be the case for u_7 ,

$$u_7 = \frac{1}{15}Q_1 + \frac{1}{75}Q_2 - \frac{5}{4}Q_3 + \frac{9}{100}Q_4 + \frac{2484}{10625}Q_5 - \frac{29}{450}d_1 + \frac{1018691}{4050000}d_2 + \frac{99719}{24000}d_3 - \frac{2507}{1000}d_4 - \frac{1053}{4000}d_5 - \frac{1404}{10625}d_6 + \frac{1863}{2750}d_7 \quad (36)$$

but not for u_8 , so that one additional commutator must be introduced:

$$d_8 = \left[Q_1 + Q_2, -\frac{46981}{8256}Q_3 + \frac{275}{1376}Q_4 - \frac{1881}{18275}Q_5 - \frac{198583}{464400}d_1 + \frac{75823}{2786400}d_2 + \frac{30107}{74304}d_3 - \frac{407}{12384}d_5 \right] \quad (37)$$

so that

$$u_8 = Q_1 + 3Q_2 + \frac{1375}{258}Q_3 + \frac{187}{516}Q_4 + \frac{220}{731}Q_5 + \frac{3850}{26703}Q_7 - \frac{59}{258}d_1 + \frac{151043}{464400}d_2 + \frac{32021}{8256}d_3 - \frac{319}{1376}d_5 + d_8. \quad (38)$$

Finally, in v one has the new commutators $[Q_1, Q_6]$ and $[Q_1, [Q_1, Q_6]]$ so that at least two additional commutators are required to reproduce it up to order $\mathcal{O}(\hbar^6)$. Let us introduce

$$d_9 = [Q_1, Q_9] \quad (39)$$

and, in order to avoid redundancies,

$$d_{10} = \left[\sum_{i=1}^4 a_{10,i} Q_i, \sum_{j=3}^7 b_{10,j} Q_j + \sum_{j=8}^{16} b_{10,j} d_{j-7} \right]. \quad (40)$$

Then

$$v = Q_1 + 3Q_2 + \frac{3}{4}Q_4 + \frac{12}{85}Q_5 + \frac{3}{44}Q_6 + \frac{43}{616}Q_8 + \sum_{i=1}^{10} \gamma_i d_i. \quad (41)$$

After expanding d_{10} , equating terms with v and solving the corresponding equations we get

$$\begin{aligned}
a_{10,1} &= \frac{1}{1000} & a_{10,2} &= \frac{105964609689}{266416480000} \\
a_{10,3} &= -\frac{864346110425653578282776169}{615375255075268247296000} & a_{10,4} &= \frac{341966417238630384261243993}{1538438137688170618240000} \\
b_{10,3} &= \frac{233929567983791656250}{1247610945171345852969} & b_{10,4} &= -\frac{36812199380273802500}{1247610945171345852969} \\
b_{10,5} &= -\frac{42626636800}{200155373857} & b_{10,6} &= -\frac{3027460000}{11773845521} \\
b_{10,7} &= \frac{6250}{621} & b_{10,8} &= -\frac{850304064427933000}{1247610945171345852969} \\
b_{10,9} &= -\frac{324431382151464725}{7189486838179272} & b_{10,10} &= -\frac{2566642496229085375}{3195327483635232} \\
b_{10,11} &= \frac{406587275}{316624} & b_{10,12} &= \frac{82453548663197675}{1597663741817616} \\
b_{10,13} &= \frac{4212930}{30583} & b_{10,14} &= \frac{577797525}{870716} \\
b_{10,15} &= -\frac{413547125}{435358} & b_{10,16} &= \frac{125}{22} \\
\gamma_1 &= -\frac{1}{2} & \gamma_2 &= \frac{84495317249601260110864639}{564319382719903156214938080} \\
\gamma_3 &= -\frac{272089389229241879933054635}{451455506175922524971950464} & \gamma_4 &= \frac{29817608309216341}{14911528256964416} \\
\gamma_5 &= \frac{30276197407357512902600687}{225727753087961262485975232} & \gamma_6 &= \frac{2782759594196403}{3600795175687430} \\
\gamma_7 &= \frac{1544992960649931}{41006702706652144} & \gamma_8 &= \frac{8252596669788325}{20503351353326072} \\
\gamma_9 &= -\frac{35055120083}{1036098405848} & \gamma_{10} &= 1
\end{aligned} \tag{42}$$

On the other hand, to reproduce \hat{v} we must introduce one additional commutator d_{11} similar to d_{10} :

$$d_{11} = \left[\sum_{i=1}^4 a_{11,i} Q_i, \sum_{j=3}^7 b_{11,j} Q_j + \sum_{j=8}^{16} b_{11,j} d_{j-7} \right]. \tag{43}$$

Then

$$\hat{v} = Q_1 + 3Q_2 + \frac{3}{4}Q_4 + \frac{12}{85}Q_5 + \frac{3}{44}Q_6 + \sum_{i=1}^9 \hat{\gamma}_i d_i + \hat{\gamma}_{11} d_{11} \tag{44}$$

with

$$\begin{aligned}
a_{11,1} &= \frac{1}{10000} & a_{11,2} &= \frac{182530798193}{4575730800000} \\
a_{11,3} &= -\frac{68659798432120392143565920855953}{423899875411478618541350400000} & a_{11,4} &= \frac{216159791919309770355211486373}{8477997508229572370827008000} \\
b_{11,3} &= \frac{7590543686660318689031250}{4031416566965816739895129} & b_{11,4} &= -\frac{1188697609320162319312500}{4031416566965816739895129} \\
b_{11,5} &= -\frac{5948450040000}{3103023569281} & b_{11,6} &= -\frac{5147697150000}{2007838780123} \\
b_{11,7} &= 0 & b_{11,8} &= -\frac{23863076643984556185000}{4031416566965816739895129} \\
b_{11,9} &= -\frac{49378501924616204885}{111459146362187976} & b_{11,10} &= -\frac{1171104867204907392125}{148612195149583968} \\
b_{11,11} &= \frac{36891785375}{2849616} & b_{11,12} &= \frac{37582182892976202625}{74306097574791984} \\
b_{11,13} &= \frac{131169950}{91749} & b_{11,14} &= \frac{6127951625}{870716} \\
b_{11,15} &= -\frac{13007096875}{1306074} & b_{11,16} &= \frac{625}{11}
\end{aligned} \tag{45}$$

and

$$\begin{aligned}
\hat{\gamma}_1 &= -\frac{1}{2} & \hat{\gamma}_2 &= \frac{2482673240896563598147417653}{16577184923363438434448770448} \\
\hat{\gamma}_3 &= -\frac{119785970219681956126484569385}{198926219080361261213385245376} & \hat{\gamma}_4 &= \frac{2543028894134407003}{1271459891835329504} \\
\hat{\gamma}_5 &= \frac{13338062312219965746250323937}{99463109540180630606692622688} & \hat{\gamma}_6 &= \frac{237303810989198421}{307028667062508545} \\
\hat{\gamma}_7 &= \frac{134172361749673629}{3496514702547156136} & \hat{\gamma}_8 &= \frac{702333383164435955}{1748257351273578068} \\
\hat{\gamma}_9 &= -\frac{543474236859}{16062710240984} & \hat{\gamma}_{11} &= 1
\end{aligned}$$

Thus the RKMK method based on DVERK is formulated in terms of only 10 commutators. The final algorithm in its optimized form reads

Algorithm 4.1

for $i = 1 : 8$ **do**

u_i given by the optimized expressions

$$k_i = hf(\exp(u_i) \cdot y_0)$$

$$Q_i = \sum_{j=1}^i V_{i,j} k_j, \text{ with } V \text{ given by (22)}$$

end do

v given by (41)

$$y_1 = \exp(v) \cdot y_0$$

\hat{v} given by (44)

$$\hat{y}_1 = \exp(\hat{v}) \cdot y_0$$

4.3 Optimized RKMK integration schemes

The same procedure can be carried out for the explicit RKMK methods based on the Runge–Kutta schemes collected in section 3.3. Next we provide the optimized expressions of the corresponding internal stages u_i and v . In all the cases the initial stage is $u_1 = 0$.

5th-order

Let us introduce the commutators

$$d_1 = [Q_1, Q_2], \quad d_2 = [Q_1, d_1], \quad d_3 = [Q_1, Q_3], \quad d_4 = [Q_1, Q_4]. \quad (46)$$

RKF45. With

$$d_5 = \left[Q_1 + Q_2, \frac{832}{2565} Q_3 - \frac{338}{2565} Q_4 + \frac{9}{100} Q_5 - \frac{1}{15} d_1 + \frac{1}{180} d_2 - \frac{104}{7695} d_3 + \frac{169}{30780} d_4 \right] \quad (47)$$

the scheme reads

$$\begin{aligned}
u_2 &= \frac{1}{4}Q_1 \\
u_3 &= \frac{3}{8}Q_1 + \frac{9}{32}Q_2 - \frac{9}{256}d_1 + \frac{3}{2048}d_2 \\
u_4 &= \frac{12}{13}Q_1 + \frac{288}{169}Q_2 + \frac{7296}{2197}Q_3 - \frac{126}{2197}d_1 - \frac{813}{17576}d_2 - \frac{1368}{2197}d_3 \\
u_5 &= Q_1 + 2Q_2 + \frac{3680}{513}Q_3 - \frac{845}{4104}Q_4 + \frac{1}{6}d_1 - \frac{157}{1248}d_2 - \frac{1250}{741}d_3 + \frac{65}{684}d_4 \\
u_6 &= \frac{1}{2}Q_1 + \frac{1}{2}Q_2 - \frac{656}{513}Q_3 + \frac{1859}{16416}Q_4 - \frac{1}{6}d_1 + \frac{1}{4992}d_2 - \frac{355}{13338}d_3 - \frac{715}{65664}d_4 \\
v &= Q_1 + 2Q_2 + \frac{320}{513}Q_3 + \frac{1183}{4104}Q_4 - \frac{1}{5}Q_5 + \frac{2}{55}Q_6 - \frac{1}{3}d_1 + \frac{1}{15}d_2 - \frac{752}{2565}d_3 \\
&\quad + \frac{1183}{41040}d_4 + d_5
\end{aligned}$$

whereas for the embedded method a new commutator is required:

$$d_6 = \left[Q_1 + Q_2, \frac{1738}{6669}Q_3 - \frac{65}{513}Q_4 + \frac{1}{10}Q_5 - \frac{89}{1248}d_1 + \frac{95}{14976}d_2 - \frac{50}{20007}d_3 + \frac{221}{49248}d_4 \right] \quad (48)$$

so that

$$\hat{v} = Q_1 + 2Q_2 + \frac{320}{513}Q_3 + \frac{1183}{4104}Q_4 - \frac{1}{5}Q_5 - \frac{1}{3}d_1 + \frac{89}{1248}d_2 - \frac{170}{741}d_3 + \frac{65}{2736}d_4 + d_6. \quad (49)$$

The integration scheme in its final form is similar to Algorithm 4.1 with the obvious modifications.

DOPRI5(4). With commutators (46) and

$$d_5 = \left[Q_1 + Q_2, -\frac{25}{36}Q_3 - \frac{5}{24}Q_4 - \frac{675}{13568}Q_5 - \frac{11}{168}Q_6 - \frac{5}{48}d_1 + \frac{1}{144}d_2 + \frac{5}{216}d_3 + \frac{1}{144}d_4 \right] \quad (50)$$

one gets

$$\begin{aligned}
u_2 &= \frac{1}{5}Q_1 \\
u_3 &= \frac{3}{10}Q_1 + \frac{9}{40}Q_2 - \frac{9}{400}d_1 + \frac{3}{4000}d_2 \\
u_4 &= \frac{4}{5}Q_1 + \frac{8}{5}Q_2 + \frac{32}{9}Q_3 - \frac{2}{75}d_1 - \frac{73}{2250}d_2 - \frac{8}{15}d_3 \\
u_5 &= \frac{8}{9}Q_1 + \frac{160}{81}Q_2 + \frac{53000}{6561}Q_3 - \frac{212}{729}Q_4 + \frac{628}{2187}d_1 - \frac{3971}{32805}d_2 - \frac{8480}{6561}d_3 + \frac{424}{3645}d_4 \\
u_6 &= Q_1 + \frac{5}{2}Q_2 + \frac{3395}{396}Q_3 - \frac{7}{88}Q_4 - \frac{5103}{18656}Q_5 + \frac{4}{33}d_1 - \frac{1103}{7920}d_2 - \frac{455}{264}d_3 + \frac{7}{80}d_4 \\
v &= u_7 = Q_1 + \frac{5}{2}Q_2 + \frac{115}{36}Q_3 + \frac{11}{24}Q_4 + \frac{189}{6784}Q_5 + \frac{11}{84}Q_6 - \frac{5}{12}d_1 + \frac{5}{48}d_2 - \frac{5}{72}d_3 \\
&\quad + \frac{1}{16}d_4 + d_5
\end{aligned}$$

whereas the embedded method is obtained with

$$\begin{aligned}
d_6 &= \left[Q_1 + Q_2, -\frac{5755}{7776}Q_3 - \frac{2929}{14400}Q_4 - \frac{22167}{542720}Q_5 - \frac{143}{2240}Q_6 - \frac{18781}{172800}d_1 + \frac{11713}{1555200}d_2 \right. \\
&\quad \left. + \frac{32813}{1166400}d_3 + \frac{7847}{1296000}d_4 \right] \\
\hat{v} &= Q_1 + \frac{5}{2}Q_2 + \frac{115}{36}Q_3 + \frac{11}{24}Q_4 + \frac{189}{6784}Q_5 + \frac{11}{84}Q_6 + \frac{1}{40}Q_7 - \frac{5}{12}d_1 + \frac{18781}{172800}d_2 \\
&\quad - \frac{185}{7776}d_3 + \frac{829}{14400}d_4 + d_6
\end{aligned} \tag{51}$$

6th-order

6th-order Butcher's method. If we introduce the commutators

$$\begin{aligned}
d_1 &= [Q_1, Q_2], & d_2 &= [Q_1, d_1], & d_3 &= [Q_1, Q_3] \\
d_4 &= \left[Q_1 + Q_2, \frac{1}{54}Q_3 + \frac{7}{1458}d_1 - \frac{7}{7776}d_2 - \frac{1}{324}d_3 \right] \\
d_5 &= [Q_1, Q_4] \\
d_6 &= \left[Q_1 + Q_2, -\frac{95}{864}Q_3 - \frac{5}{48}Q_4 - \frac{1475}{23328}d_1 + \frac{515}{31104}d_2 + \frac{415}{10368}d_3 + \frac{5}{288}d_5 \right] \\
d_7 &= \left[Q_1 + Q_2, -\frac{187}{1152}Q_3 + \frac{11}{64}Q_4 - \frac{1}{24}Q_5 + \frac{473}{31104}d_1 - \frac{83}{20736}d_2 + \frac{169}{6912}d_3 - \frac{1}{32}d_5 \right] \\
d_8 &= \left[Q_1 + Q_2, -\frac{263}{468}Q_3 + \frac{47}{78}Q_4 + \frac{697}{12636}d_1 - \frac{673}{33696}d_2 - \frac{139}{2808}d_3 - \frac{7}{234}d_5 \right] \\
d_9 &= [Q_1, Q_7] \\
d_{10} &= \left[\sum_{i=1}^4 a_{10,i}Q_i, \sum_{j=3}^7 b_{10,j}Q_j + \sum_{j=8}^{16} b_{10,j}d_{j-7} \right]
\end{aligned} \tag{52}$$

with

$$\begin{aligned}
a_{10,1} &= 1 & a_{10,2} &= \frac{12414111}{2862373} \\
a_{10,3} &= -\frac{3344498516974806342}{1148667336698745595} & a_{10,4} &= \frac{852537360423215772}{229733467339749119} \\
b_{10,3} &= -\frac{1211654167286701}{4383577654622464} & b_{10,4} &= \frac{1808327572040239}{6575366481933696} \\
b_{10,5} &= \frac{20036611}{620705550} & b_{10,6} &= \frac{5}{6} \\
b_{10,7} &= -\frac{37210849}{4965644400} & b_{10,8} &= \frac{2368386261234527}{118356596674806528} \\
b_{10,9} &= -\frac{693501437}{38533400544} & b_{10,10} &= -\frac{5821103891}{192667002720} \\
b_{10,11} &= \frac{183379}{15520} & b_{10,12} &= -\frac{686219695}{19266700272} \\
b_{10,13} &= \frac{3883}{4850} & b_{10,14} &= \frac{14}{25} \\
b_{10,15} &= \frac{1469}{77600} & b_{10,16} &= \frac{13}{2400}
\end{aligned} \tag{53}$$

the successive stages are

$$\begin{aligned}
u_2 &= \frac{1}{2}Q_1 \\
u_3 &= \frac{2}{3}Q_1 + \frac{4}{9}Q_2 - \frac{1}{9}d_1 + \frac{1}{108}d_2 \\
u_4 &= \frac{1}{3}Q_1 + \frac{1}{9}Q_2 - \frac{1}{12}Q_3 - \frac{1}{27}d_1 + \frac{7}{2916}d_2 + \frac{1}{108}d_3 + d_4 \\
u_5 &= \frac{5}{6}Q_1 + \frac{25}{36}Q_2 - \frac{55}{48}Q_3 + \frac{15}{8}Q_4 + \frac{25}{216}d_1 - \frac{935}{46656}d_2 + \frac{175}{1728}d_3 - \frac{5}{24}d_5 + d_6 \\
u_6 &= \frac{1}{6}Q_1 + \frac{1}{36}Q_2 - \frac{5}{16}Q_3 + \frac{3}{8}Q_4 + \frac{1}{10}Q_5 + \frac{1}{24}d_1 - \frac{461}{31104}d_2 + \frac{91}{1152}d_3 - \frac{7}{64}d_5 + d_7 \\
u_7 &= Q_1 + Q_2 + \frac{105}{52}Q_3 - \frac{22}{13}Q_4 + \frac{112}{195}Q_5 + \frac{80}{39}Q_6 - \frac{47}{117}d_1 + \frac{77}{972}d_2 - \frac{181}{468}d_3 + \frac{31}{78}d_5 + d_8 \\
v &= Q_1 + Q_2 + \frac{3}{4}Q_3 - \frac{3}{25}Q_5 - \frac{7}{5}Q_6 + \frac{13}{200}Q_7 + \sum_{i=1}^{10} \gamma_i d_i
\end{aligned}$$

with

$$\begin{aligned}
\gamma_1 &= -\frac{1}{6} & \gamma_2 &= \frac{2394909222187244419}{28701474693640583040} & \gamma_3 &= -\frac{1033648621490941081}{1063017581245947520} \\
\gamma_4 &= -\frac{2529352064163}{25688933696} & \gamma_5 &= \frac{138361293267732931}{1594526371868921280} & \gamma_6 &= -\frac{336377495913}{40138958900} \\
\gamma_7 &= -\frac{201240072}{103450925} & \gamma_8 &= -\frac{1525556859489}{642223342400} & \gamma_9 &= -\frac{62086297}{2482822200} \\
\gamma_{10} &= 1
\end{aligned} \tag{54}$$

Here, as is the case with DVERK, one additional commutator (d_8) is necessary to write u_7 (it cannot be expressed as a linear combination of d_1, \dots, d_7).

7th-order

The optimization process of the 7th-order methods considered in section 3.3 is technically much more difficult. Not only they involve more stages than the schemes analyzed before but also all the computations for the internal stages have to be carried out up to order $\mathcal{O}(h^6)$, whereas in the expression of v one has to consider also terms of order $\mathcal{O}(h^7)$. Taking into account the explosive growth of the dimensions of the corresponding homogeneous subspaces of the graded free Lie algebra, the optimization of the resulting schemes constitutes a formidable task.

7th order Butcher method. The internal stages u_i , $i = 1, \dots, 9$ can be expressed in terms of 15 different commutators. In fact, the absolute minimum is 13, but we have not obtained real solutions and thus two additional commutators are necessary, one for u_5 and one for u_9 . In principle, at least two more commutators are required in v but, unfortunately, we have not been able to solve the 61 nonlinear equations in the coefficients, so that we have introduced additional commutators. It turns out that these equations can be solved in sequence with six more, conveniently chosen commutators. Therefore the corresponding RKMK scheme can be expressed with a total number of 21 commutators. This, although not optimal in a strict sense, is a considerable improvement with respect to the original implementation in terms of the k_i . The coefficients of the method are available from the authors.

Method	p	s	Orig	FLA	New
RKF45	5	6	20	11	5 (6)
DOPRI5(4)	5	6 (7)	20 (24)	12	5 (6)
DVERK	6	8	28	26	10 (11)
Butcher6	6	7	24	26	10
Butcher7	7	9	48	60	21
RKF7	7	11	60	64	23

Table 1: Number of commutators involved in some RKMK methods. Columns indicate order (p), number of stages (s), the number of commutators as presented originally in [7] (Orig), the number indicated by the free Lie algebra approach of [8] (FLA), and the number obtained by the approach of this paper (New). The numbers in parenthesis refer to the embedded pair (whenever it differs).

Runge–Kutta–Fehlberg 7(8). Now there are 11 stages and 17 commutators are required to write u_1, \dots, u_{11} up to order $\mathcal{O}(h^6)$ instead of 15, the absolute minimum in this case: we need one more for u_5 and u_{11} . With respect to v , the 64 equations involved can be solved quite easily by introducing 6 additional commutators. Thus the method requires a total of 23 commutators. There remains as an open question to prove that this is, in fact, the minimum number. The final expressions for the stages of the method are collected in the Appendix.

5 Concluding remarks

We have presented new versions of Lie group integrators of Runge–Kutta–Munthe-Kaas type which use a lower number of commutators per stage than what can be found in the literature. We have summarized the results in Table 1. Notice that the numbers given for the new methods are not in all cases proved to be optimal, but they represent a substantial reduction compared to what has been previously known. Note also that for the Runge-Kutta-Fehlberg method RKF78, we have only presented optimised results for the 7th order method, which is using only the first 11 stages of RKF78.

We believe that there is reason to be cautious in interpreting these numbers too rigidly. For instance, it is not known to which extent the reduction of complexity will affect the quality of the numerical approximation. Also, one should keep in mind that in some cases, the savings obtained by reducing the number of commutators could be insignificant compared for instance to the cost of calculating exponentials. Nevertheless, we still think that there are important problems for which the obtained reduced commutator counts may substantially improve the efficiency of the Lie group integrators presented here.

Acknowledgments

The work of FC has been partially supported by Fundació Bancaixa under project P1 1B2002-22. FC would like to thank the Center for Advanced Study, Oslo, Norway for its hospitality.

A Appendix

For completeness, in this appendix we collect the optimized expressions for the 11 stages of the 7th-order method RKF7, whereas the 64 terms of v up to order $\mathcal{O}(h^6)$ are written with only 6 additional commutators.

As usual, we start by introducing the commutators

$$\begin{aligned}
d_1 &= [Q_1, Q_2], & d_2 &= [Q_1, d_1] \\
d_3 &= [Q_1, d_2], & d_4 &= [Q_1, d_3] \\
d_5 &= [Q_1, Q_3] \\
d_6 &= \left[Q_1 + \frac{3}{2}Q_2 + 2Q_3, -\frac{1}{288}Q_3 - \frac{1}{6912}d_1 + \frac{13}{1679616}d_2 + \frac{1}{7776}d_5 \right] \\
d_7 &= [Q_1, Q_4] & d_8 &= [Q_1, d_5] \\
d_9 &= \left[Q_1 + \frac{9}{4}Q_2 + \frac{153}{22}Q_3 + \frac{108}{11}Q_4, -\frac{125}{3456}Q_3 - \frac{25}{384}Q_4 - \frac{275}{331776}d_1 + \frac{19025}{322486272}d_2 \right. \\
&\quad \left. - \frac{1225}{1492992}d_5 + \frac{125}{288}d_6 + \frac{25}{6912}d_7 + \frac{875}{4478976}d_8 \right] \\
d_{10} &= [Q_1, Q_5] \\
d_{11} &= \left[Q_1 + \frac{3573}{608}Q_2 + \frac{604631}{13072}Q_3 + \frac{276709}{6536}Q_4, -\frac{817}{6352}(Q_3 + Q_4) - \frac{95}{4764}Q_5 - \frac{817}{203264}d_1 \right. \\
&\quad \left. + \frac{994513}{526860288}d_2 + \frac{229105}{5488128}d_5 + \frac{13}{4}d_6 + \frac{181}{4608}d_7 + \frac{8039}{5971968}d_8 + \frac{7}{20}d_9 + \frac{5}{1728}d_{10} \right] \\
d_{12} &= [Q_1, Q_6] \\
d_{13} &= \left[Q_1 + \frac{7569}{224}Q_2 + \frac{5463977}{12208}Q_3 + \frac{2594485}{6104}Q_4, -\frac{95375}{363312}(Q_3 + Q_4) + \frac{23975}{272484}Q_5 \right. \\
&\quad \left. - \frac{875}{15138}Q_6 - \frac{95375}{11625984}d_1 + \frac{1176601625}{30134550528}d_2 + \frac{339375125}{313901568}d_5 + \frac{18875}{108}d_6 + \frac{106625}{124416}d_7 \right. \\
&\quad \left. + \frac{11488375}{161243136}d_8 + \frac{1375}{108}d_9 - \frac{4775}{46656}d_{10} + \frac{125}{2592}d_{12} \right] \\
d_{14} &= \left[Q_1 + \frac{4059}{928}Q_2 + \frac{443333}{3728}Q_3 + \frac{783838}{6757}Q_4, -\frac{6757}{194832}(Q_3 + Q_4) + \frac{109127}{2191860}Q_5 \right. \\
&\quad \left. - \frac{4727}{109593}Q_6 - \frac{13}{2160}Q_7 - \frac{6757}{6234624}d_1 + \frac{9138887}{12120109056}d_2 + \frac{2005897}{252502272}d_5 - \frac{763}{324}d_6 \right. \\
&\quad \left. + \frac{241}{31104}d_7 - \frac{424057}{241864704}d_8 - \frac{107}{2025}d_9 + \frac{49}{174960}d_{10} + \frac{49}{17496}d_{12} \right] \\
d_{15} &= \left[Q_1 + \frac{554841}{108128}Q_2 + \frac{234204551}{1920512}Q_3 + \frac{24812181275}{209335808}Q_4, -\frac{3270872}{1664523}(Q_3 + Q_4) \right. \\
&\quad \left. + \frac{143411518}{74903535}Q_5 - \frac{3875713}{2140101}Q_6 - \frac{779}{2700}Q_7 - \frac{1}{4}Q_8 - \frac{408859}{6658092}d_1 + \frac{153077696507}{3313492697088}d_2 \right. \\
&\quad \left. + \frac{26524129865}{34515548928}d_5 - \frac{13157}{162}d_6 + \frac{47345}{62208}d_7 - \frac{16288645}{241864704}d_8 + \frac{6797}{4050}d_9 + \frac{35459}{349920}d_{10} + \frac{6469}{69984}d_{12} \right] \\
d_{16} &= \left[Q_1 + \frac{1451421}{284000}Q_2 + \frac{10391045477}{65660800}Q_3 + \frac{50836665601}{328304000}Q_4, \frac{2564875}{4354263}(Q_3 + Q_4) \right. \\
&\quad \left. - \frac{10864775}{13062789}Q_5 + \frac{20456875}{26125578}Q_6 + \frac{437}{3600}Q_7 - \frac{11}{36}Q_8 + \frac{1}{36}Q_9 + \frac{2564875}{139336416}d_1 - \right. \\
&\quad \left. \frac{87358335197}{5778559844352}d_2 - \frac{15428461715}{60193331712}d_5 + \frac{1360}{27}d_6 - \frac{32209}{124416}d_7 + \frac{5532815}{161243136}d_8 \right. \\
&\quad \left. + \frac{1097}{2700}d_9 - \frac{2759}{77760}d_{10} - \frac{1049}{23328}d_{12} \right] \\
d_{17} &= \left[Q_1 + \frac{7107759}{705056}Q_2 + \frac{1901549032033}{10595581568}Q_3 + \frac{1830338763865}{10595581568}Q_4, -\frac{82777981}{32379791}(Q_3 + Q_4) \right. \\
&\quad \left. + \frac{776685283}{485696865}Q_5 - \frac{235731067}{194278746}Q_6 - \frac{3}{16}Q_7 + \frac{33}{41}Q_8 - \frac{3}{41}Q_9 - \frac{82777981}{1036153312}d_1 \right. \\
&\quad \left. + \frac{5805480092969}{42971350155264}d_2 + \frac{1417102831679}{447618230784}d_5 + \frac{33703}{82}d_6 + \frac{520567}{188928}d_7 + \frac{36131623}{244850688}d_8 \right. \\
&\quad \left. + \frac{28829}{820}d_9 - \frac{23767}{118080}d_{10} + \frac{3181}{17712}d_{12} \right]
\end{aligned}$$

Then the intermediate stages read ($u_1 = 0$)

$$\begin{aligned}
u_2 &= \frac{2}{27}Q_1 \\
u_3 &= \frac{1}{9}Q_1 + \frac{1}{12}Q_2 - \frac{1}{324}d_1 + \frac{1}{26244}d_2 - \frac{1}{286978140}d_4 \\
u_4 &= \frac{1}{6}Q_1 + \frac{3}{16}Q_2 + \frac{1}{8}Q_3 - \frac{1}{192}d_1 + \frac{1}{20736}d_2 - \frac{1}{559872}d_3 - \frac{29}{453496320}d_4 - \frac{1}{288}d_5 + d_6 \\
u_5 &= \frac{5}{12}Q_1 + \frac{75}{64}Q_2 + \frac{75}{32}Q_3 + \frac{25}{16}Q_4 - \frac{125}{1536}d_1 + \frac{25}{12288}d_2 - \frac{10625}{322486272}d_3 + \frac{13355}{5804752896}d_4 \\
&\quad - \frac{725}{6912}d_5 - \frac{25}{384}d_7 + \frac{2425}{1492992}d_8 + d_9 \\
u_6 &= \frac{1}{2}Q_1 + \frac{27}{16}Q_2 + \frac{33}{8}Q_3 + 3Q_4 + \frac{1}{5}Q_5 - \frac{9}{64}d_1 + \frac{817}{203264}d_2 - \frac{38249}{87810048}d_3 - \frac{23639}{403107840}d_4 \\
&\quad - \frac{5115}{12704}d_5 - \frac{981}{3176}d_7 + \frac{33}{12704}d_8 - \frac{69}{3176}d_{10} + d_{11} \\
u_7 &= \frac{5}{6}Q_1 + \frac{75}{16}Q_2 + \frac{475}{24}Q_3 + \frac{50}{3}Q_4 - \frac{65}{27}Q_5 + \frac{125}{54}Q_6 - \frac{125}{192}d_1 + \frac{95375}{11625984}d_2 + \frac{10698125}{502242508}d_3 \\
&\quad - \frac{204025}{272097792}d_4 - \frac{952625}{2422208}d_5 - \frac{70625}{20184}d_7 - \frac{116125}{2906496}d_8 + \frac{117175}{181656}d_{10} - \frac{94625}{181656}d_{12} + d_{13} \\
u_8 &= \frac{1}{6}Q_1 + \frac{3}{16}Q_2 + \frac{1}{8}Q_3 - \frac{1}{27}Q_5 + \frac{1}{54}Q_6 + \frac{13}{900}Q_7 - \frac{1}{192}d_1 + \frac{6757}{6234624}d_2 - \frac{770345}{897785856}d_3 \\
&\quad - \frac{15111713}{261213880320}d_4 + \frac{417}{14432}d_5 + \frac{1051}{32472}d_7 - \frac{8981}{9351936}d_8 - \frac{1916}{109593}d_{10} + \frac{26473}{1753488}d_{12} + d_{14} \\
u_9 &= \frac{2}{3}Q_1 + 3Q_2 + 10Q_3 + 8Q_4 - \frac{32}{135}Q_5 + \frac{14}{27}Q_6 + \frac{67}{90}Q_7 + 3Q_8 - \frac{1}{3}d_1 + \frac{408859}{6658092}d_2 \\
&\quad - \frac{1194089405}{30680487936}d_3 - \frac{209404337}{65303470080}d_4 + \frac{145006}{554841}d_5 + \frac{268304}{554841}d_7 + \frac{10793959}{639176832}d_8 \\
&\quad - \frac{208868939}{299614140}d_{10} + \frac{8609503}{17120808}d_{12} + d_{15} \\
u_{10} &= \frac{1}{3}Q_1 + \frac{3}{4}Q_2 + \frac{7}{6}Q_3 + \frac{2}{3}Q_4 + \frac{8}{135}Q_5 - \frac{1}{54}Q_6 - \frac{19}{60}Q_7 + \frac{8}{3}Q_8 - \frac{1}{12}Q_9 - \frac{1}{24}d_1 \\
&\quad - \frac{2564875}{139336416}d_2 + \frac{7729089505}{481546653696}d_3 + \frac{114375137}{87071293440}d_4 - \frac{1337051}{1935228}d_5 - \frac{962471}{1451421}d_7 \\
&\quad + \frac{3691597}{1114691328}d_8 + \frac{45253181}{174170520}d_{10} - \frac{15255787}{69668208}d_{12} + d_{16} \\
u_{11} &= Q_1 + \frac{27}{4}Q_2 + \frac{69}{2}Q_3 + 30Q_4 - 8Q_5 + \frac{13}{2}Q_6 + \frac{2313}{4100}Q_7 + \frac{36}{41}Q_8 + \frac{9}{164}Q_9 + \frac{18}{41}Q_{10} - \frac{9}{8}d_1 \\
&\quad + \frac{82777981}{1036153312}d_2 - \frac{85464151441}{3580945846272}d_3 - \frac{519502109}{132219371520}d_4 - \frac{802180761}{129519164}d_5 - \frac{176260347}{32379791}d_7 \\
&\quad + \frac{813507603}{8289226496}d_8 + \frac{413374247}{259038328}d_{10} - \frac{690004741}{518076656}d_{12} + d_{17}
\end{aligned}$$

If we denote $r = \sqrt{6601}$ and introduce

$$\begin{aligned}
d_{18} &= [Q_1 + a_{1,1}Q_2 + a_{1,2}Q_3 + a_{1,3}Q_4, b_{1,1}Q_3 + b_{1,2}Q_4 + b_{1,3}Q_7 + b_{1,4}Q_8 + \\
&\quad b_{1,5}Q_9 + b_{1,6}d_1 + b_{1,7}d_5 + b_{1,8}d_7 + b_{1,9}d_8 + b_{1,10}d_{10} + b_{1,11}d_{12}] \\
d_{19} &= [Q_1 + a_{2,1}Q_2 + a_{2,2}d_2, b_{2,1}Q_3 + b_{2,2}Q_4 + b_{2,3}d_{18}] \\
d_{20} &= [Q_1 + a_{3,1}Q_2 + a_{3,2}Q_4 + a_{3,3}Q_5 + a_{3,4}Q_6, b_{3,1}Q_5 + b_{3,2}Q_6 + b_{3,3}d_1 + \\
&\quad b_{3,4}d_5 + b_{3,5}d_7 + b_{3,6}d_{19}] \\
d_{21} &= [Q_1, b_{4,1}Q_7 + b_{4,2}Q_8 + b_{4,3}Q_9 + b_{4,4}Q_{10} + b_{4,5}Q_{11} + b_{4,6}d_4 + b_{4,7}d_7 + \\
&\quad b_{4,8}d_8 + b_{4,9}d_{10} + b_{4,10}d_{12}] \\
d_{22} &= [Q_2, b_{5,1}Q_3 + b_{5,2}Q_4 + b_{5,3}Q_5 + b_{5,4}Q_6 + b_{5,5}Q_7 + b_{5,6}Q_8 + b_{5,7}Q_9 + \\
&\quad b_{5,8}d_1 + b_{5,9}d_3 + b_{5,10}d_5 + b_{5,11}d_7 + b_{5,12}d_8 + b_{5,13}d_{10} + b_{5,14}d_{12}] \\
d_{23} &= [Q_3, b_{6,1}Q_4 + b_{6,2}Q_5 + b_{6,3}Q_6 + b_{6,4}d_1 + b_{6,5}d_2 + b_{6,6}d_5 + b_{6,7}d_7]
\end{aligned}$$

with

$$\begin{aligned}
a_{1,1} &= -\frac{9(-109+r)}{224} & a_{1,2} &= \frac{143(-54669+721r)}{319872} \\
a_{1,3} &= \frac{-332733+4417r}{11760} & b_{1,1} &= \frac{65239-1035r}{612} \\
b_{1,2} &= \frac{1082-18r}{9} & b_{1,3} &= -\frac{61(-541+9r)}{88200} \\
b_{1,4} &= \frac{109(-541+9r)}{52920} & b_{1,5} &= \frac{13(-541+9r)}{13230} \\
b_{1,6} &= 1 & b_{1,7} &= -\frac{5(-2483+47r)}{2856} \\
b_{1,8} &= \frac{541-9r}{105} & b_{1,9} &= \frac{-1643+7r}{85680} \\
b_{1,10} &= \frac{46(-541+9r)}{33075} & b_{1,11} &= -\frac{173(-541+9r)}{158760} \\
a_{2,1} &= -\frac{9(1+r)}{280} & a_{2,2} &= \frac{19(16941271+190471r)}{10380140400} \\
b_{2,1} &= \frac{147(-35947459+412759r)}{31067296} & b_{2,2} &= \frac{147(-16941271+190471r)}{12563980} \\
b_{2,3} &= -\frac{63(541+9r)}{484000} & a_{3,1} &= -\frac{9(1679+9r)}{1400} \\
a_{3,2} &= 1 & a_{3,3} &= -\frac{157(34861997+437825r)}{1914878490} \\
a_{3,4} &= \frac{121(34861997+437825r)}{2042537056} & b_{3,1} &= \frac{7584}{175} \\
b_{3,2} &= -\frac{969}{35} & b_{3,3} &= -\frac{9(-34861997+437825r)}{9137440} \\
b_{3,4} &= \frac{-83228835023+101125955r}{2174710720} & b_{3,5} &= \frac{-6137147431+9333079r}{175895720} \\
b_{3,6} &= -\frac{1}{42} & b_{4,1} &= -\frac{39}{200} \\
b_{4,2} &= \frac{19}{40} & b_{4,3} &= \frac{7}{40} \\
b_{4,4} &= -\frac{153}{140} & b_{4,5} &= -\frac{41}{1680} \\
b_{4,6} &= -\frac{1}{2240} & b_{4,7} &= \frac{1643}{70} \\
b_{4,8} &= -\frac{3(141797+2303r)}{8228000} & b_{4,9} &= -\frac{4}{15} \\
b_{4,10} &= \frac{11}{60} & b_{5,1} &= -\frac{81(-1475191687+20728575r)}{3106729600} \\
b_{5,2} &= -\frac{81(-6235001+88830r)}{11421800} & b_{5,3} &= \frac{27(273857+1422r)}{153125} \\
b_{5,4} &= -\frac{27(561917+2907r)}{490000} & b_{5,5} &= -\frac{2997}{28000} \\
b_{5,6} &= \frac{1971}{5600} & b_{5,7} &= \frac{27}{224} \\
b_{5,8} &= -\frac{81(-283691+3689r)}{1120000} & b_{5,9} &= \frac{729(4913+37r)}{677600000} \\
b_{5,10} &= -\frac{9(69001834829761+240725606931r)}{15222975040000} & b_{5,11} &= -\frac{9(458362152589+1354886019r)}{111933640000} \\
b_{5,12} &= \frac{27(4329437+27113r)}{1645600000} & b_{5,13} &= -\frac{639}{3500} \\
b_{5,14} &= \frac{243}{2240} & b_{6,1} &= -\frac{81}{50} \\
b_{6,2} &= \frac{4674}{875} & b_{6,3} &= -\frac{1221}{350} \\
b_{6,4} &= -\frac{9(-210655044563+2869625183r)}{683480512000} & b_{6,5} &= \frac{81(256567+855r)}{548765440} \\
b_{6,6} &= -\frac{20361}{5600} & b_{6,7} &= -\frac{1119}{350}
\end{aligned}$$

then

$$\begin{aligned}
v = & Q_1 + \frac{27}{4}Q_2 + \frac{69}{2}Q_3 + 30Q_4 - 8Q_5 + \frac{13}{2}Q_6 + \frac{12}{25}Q_7 - \frac{1}{2}Q_8 - \frac{7}{20}Q_9 + \frac{78}{35}Q_{10} \\
& + \frac{41}{840}Q_{11} - \frac{9}{8}d_1 + \frac{9(-34861997 + 437825r)}{9137440}d_2 + \frac{3(14386 + 189r)}{484000}d_3 - \frac{3(541 + 9r)}{968000}d_4 \\
& + \frac{7(716062519 - 8667939r)}{31067296}d_5 + \frac{2389854997 - 27999237r}{12563980}d_7 + \frac{416854876 + 83349r}{14399000}d_8 \\
& - \frac{7052}{175}d_{10} + \frac{2131}{84}d_{12} + d_{19} + d_{20} + d_{21} + 10d_{22} + 10d_{23}
\end{aligned}$$

References

- [1] S. Blanes, F. Casas, and J. Ros. High order optimized geometric integrators for linear differential equations. *BIT*, 42(2):262–284, 2002.
- [2] J.C. Butcher. *The Numerical Analysis of Ordinary Differential Equations*. John Wiley, Chichester, 1987.
- [3] E. Celledoni, A. Iserles, S. P. Nørsett, and B. Orel. Complexity theory for Lie-group solvers. *J. of Complexity*, 18(1), 2002.
- [4] E. Hairer, S. P. Nørsett, and G. Wanner. *Solving Ordinary Differential Equations I, Nonstiff Problems*. Springer-Verlag, Second revised edition, 1993.
- [5] A. Iserles, H. Z. Munthe-Kaas, S. P. Nørsett, and A. Zanna. Lie-group methods. *Acta Numerica*, 9:215–365, 2000.
- [6] A. Iserles and S. P. Nørsett. On the solution of linear differential equations in Lie groups. *Phil. Trans. Royal Soc. A*, 357:983–1020, 1999.
- [7] H. Munthe-Kaas. High order Runge–Kutta methods on manifolds. *Appl. Numer. Math.*, 29:115–127, 1999.
- [8] H. Munthe-Kaas and B. Owren. Computations in a free Lie algebra. *Phil. Trans. Royal Soc. A*, 357:957–981, 1999.